



MOTION SENSOR WITH AUDIO JACK BASE



SETTINGS

DEFAULT ADJUSTMENTS

DETECTION AREA	100%	25% – 100%
HOLDTIME	10min	5s – 120min
DAYLIGHT THRESHOLD	DISABLE	2 – 400Lux
STAND-BY DIMMING LEVEL	10%	10 – 50%
STAND-BY PERIOD	0s	0s – $+\infty$



Using remote you can adjust: detection area, hold time, daylight threshold, standby dimming level, standby period.



The sensor can be installed at the maximum height of 13ft.



The sensor is compatible with ASD Battery Back-up.

ASD-08MW

Model	Watts	Voltage	Dimmable	Dimensions (LxWxH)	Finish
ASD-08MW-WH	0,36W	12V	0-10V	2-5/8" x 3/4" x 1"	White

